Termination SMA

ANNE-50+

 50Ω

DC to 18000 MHz

Maximum Ratings

Operating Temperature -55°C to 100°C -55°C to 100°C Storage Temperature Permanent damage may occur if any of these limits are exceeded.

Features

- wideband coverage, DC to 18000 MHz
- return loss, 35 dB typ. up to 4000 MHz and 27 dB typ. 10000 to 18000 MHz
- rugged construction

CASE STYLE: LL561 Connectors Model SMA-Male ANNE-50+


+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Applications

- cellular communications
- · satellite communications
- test set-up
- · defense & radar

Outline Drawing



Outline Dimensions (inch mm)

wt	С	В	Α
grams	0.35	0.37	0.58
4.0	8.89	9.40	14.73



To order ANNE-50+ with 31/2 length chain and end coupling with .130" diameter mtg. hole, use part no. ANNE-50CN+. Price is \$11.95, Qty. (1-9)


Electrical Specifications T_{AMB}=25°C

FREQUENCY (MHz)	IMPEDANCE (OHMS)	RETURN LOSS (dB) MIN.			POWER RATING* (W)
		DC-4 4- GHz GH		12-18 GHz	
DC-18000	50	30 27	7 23	21	1.0

^{*}At 50°C, derate linearly to 350mW at 100°C.

Typical Performance Data

Frequen (MHz)		s
100	51.21	
596	46.64	
1072	43.38	
2024	38.95	
2800	36.93	
3400	35.82	
4000	35.20	
4800	34.92	
6400	35.97	
8000	40.29	
10000	45.79	
12000	34.97	
14000	30.16	
16000	27.19	
18000	23.24	



- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

 B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

 C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits website at www.minicircuits.com/WCLStore/terms.jsp